



**123 Bernard Street
CHELTENHAM VIC 3192**

Tel: + 613 9532 6000

Tel: + 613 9553 6100

Fax: + 613 9532 6001

www.iceignition.com

7 Amp 1 Step (7061L) Ignition Box - Wiring Notes

Distributor to module loom:

- * Supplied finished - simply connect at both ends - no termination necessary.
- * Ensure distributor to module loom is routed separately from module to coil loom and high tension wires.

Module to coil loom (supplied finished). Please ensure the following:

- * Orange wire to coil positive (run direct to ignition coil - do not splice with any other wires).
- * Green wire to coil negative (run direct to ignition coil - do not splice with any other wires).
- * Black wire to earth / ground (run direct to engine block - do not splice with any other wires).
- * Be sure to keep the earth / ground wire from the ICE modules as short as possible. Always run the earth / ground wire from the ignition module (and voltage booster if fitted), to somewhere on the engine block, same as the battery earth / ground cable as per the instructions below. This is the only way to guarantee proper earth / ground.

Optional features:

- * Gray (single) wire = Tach Output (12 volt square wave).
- * White (single) wire = Not used on 7061L.
- * Red wire: Connects to brown, purple and pink . See also directly below.
- * Brown wire: When cut = 6 cylinder mode.
- * Purple wire: When cut = 4 cylinder mode.
- * Pink wire = Uncut, box operates in distributor mode. Cut this wire to activate crank trigger mode.
- * Note: If both the brown and purple wires are cut, box will function in 4 cylinder mode.
- * Note: When brown and purple wires are connected, box functions in 8 cylinder mode.

Power supply to coil positive - no booster or inc booster 2316 / 2216 - ideal:

- * Supply 12 volts switched (13.8 - 14.8 volts from alternator) to coil positive or booster (if fitted) via ignition switch.
- * If vehicle has ballast resistor or resistor wire, by-pass these and feed direct voltage to coil or red wire of booster.
- * Never leave original wire from the ignition switch connected to the coil positive if booster fitted (refer diagram).
- * Do not try to power anything but a single coil with the booster.
- * If wired correctly, two wires go to coil positive and one wire goes to coil negative.

Earth / Ground:

THE IMPORTANCE OF THIS STEP CANNOT BE OVER EMPHASIZED AND WILL VOID THE WARRANTY ON THE IGNITION IF IT IS NOT FOLLOWED.

- * Battery negative cable **MUST** run direct to a bare metal bolt boss on the engine block (should also be attached to body) as a single cable.
- * If the battery is mounted in the front of the vehicle the cable must be a minimum of 12mm - 13mm in diameter including the shielding, and must consist of a fine strand copper core.
- * If the battery is mounted in the rear of the vehicle the cable must be a minimum of 14mm to 15mm in diameter including the shielding, and must consist of a fine strand copper core.
- * For street cars, if you currently have the battery earth / ground cable running from the battery negative to the chassis and chassis to the engine and are relying on the body / roll cage to make the connection for earth / ground, **DO NOT** assume that because your existing ignition works like this, that the ICE Ignition will also work. You will void your warranty and quite possibly have to buy replacement parts.
- * For race cars, if you currently have the battery earth / ground cable running from the battery negative to the roll cage and are relying on the roll cage and aluminum engine plates to make the connection for earth / ground, **DO NOT** assume that because your existing ignition works like this, that the ICE Ignition will also work. You will void your warranty and quite possibly have to buy replacement parts.

Timing:

- * Initial timing = Total timing. No advance curve. Locked timing.

General:

- * Keep both looms routed away from the high tension wires.
- * These measures are to ensure no noise enters the loom and disrupts the microprocessor inside the unit.
- * Mount the unit using the vibration mounts supplied, inside the vehicle cabin, away from heat and moisture.
- * Avoid soldering wires, as they become brittle where the solder ends, flex at that point, then break.
- * To ensure unit functions correctly, the above steps must be adhered to.